

# UP1302C-12

UP1302C-12



UP1302C-12 internal power supply for CCR1036 series.

## Usage

UP1302C-12 act as a replacement power unit for the following devices, only r2 revisions:

CCR1036-12G-4S

CCR1036-12G-4S-EM

CCR1036-8G-2S+

CCR1036-8G-2S+EM

## Specifications

Open frame PSU 12 V DC 10.8 A 130 W, 90-264 Vac 90 % 55x106x34 mm.

## Installing

Each of the units comes in ESD protective packaging. Installing should be done by a qualified person, please follow safety precautions when handling electrical equipment:

1. Use a wrist grounding strap when unpacking and working with electrical components to avoid electrical discharge (ESD) damage;
2. Remove the top cover from the CCR1036 device to access the power supply unit;
3. Unplug wires from the supply unit leading to PCB;
4. Unscrew four screws and remove the old unit;
5. Place UP1302C-12 into the CCR and secure it with previously removed screws;
6. Attach supply cable to the white connector;
7. Install to cover into its original position and secure with screws.

## Safety Notice



Electric shock hazard. This equipment is to be serviced by trained personnel only.

For more information about this product visit our web page: <https://mikrotik.com/product/UP1302C-12>

## UKCA marking



## Eurasian Conformity Mark

Информация о дате изготовления устройства указана в конце серийного номера на его наклейке через дробь. Первая цифра означает номер года (последняя цифра года), две последующие означают номер недели.

Изготовитель: Mikrotikls SIA, Aizkraukles iela 23, Riga, LV-1006, Латвия, [support@mikrotik.com](mailto:support@mikrotik.com). Сделано в Китае, Латвии или Литве. См. на упаковке.

Для получения подробных сведений о гарантийном обслуживании обратитесь к продавцу. Информация об импортерах продукции MikroTik в Российскую Федерацию: <https://mikrotik.com/buy/europe/russia>

Продукты MikroTik, которые поставляются в Евразийский таможенный союз, оцениваются с учетом соответствующих требований и помечены знаком ЕАС, как показано ниже:



## Norma Oficial Mexicana

EFICIENCIA ENERGETICA CUMPLE CON LA NOM-029-ENER-2017.

La operacion de este equipo esta sujeta a las siguientes dos condiciones:

- Es posible que este equipo o dispositivo no cause interferencia perjudicial y.
- Este equipo debe aceptar cualquier interferencia, incluyendo la que pueda causar su operacion no deseada.

Fabricante: Mikrotikls SIA, Brivibas gatve 214i, Riga, LV-1039, Latvia.

País De Origen: Letonia; Lituania; China (Republica Popular); Estados Unidos De America; Mexico.

Por favor contacte a su distribuidor local para preguntas regionales específicas. La lista de importadores se puede encontrar en nuestra página de inicio – <https://mikrotik.com/buy/latinamerica/mexico>.

## CE Declaration of Conformity

Manufacturer: Mikrotikls SIA, Brivibas gatve 214i Riga, Latvia, LV1039.

The full text of the EU declaration of conformity is available at the following internet address: <https://mikrotik.com/products>



*Note. The information contained here is subject to change. Please visit the product page on [www.mikrotik.com](http://www.mikrotik.com) for the most up to date version of this document.*